COACH KIT

- EPak-XR Worn on belt, Lazer-Pro wireless bone conduction headset, Cyber Plug-In (backup) headset.

CATCHER KIT

- PXR worn on back, Diamonds earbuds, SST Plug-In (backup) earbuds.

PLAYER/ PITCHER KIT

- PXR worn on wrist, The Edge wireless bone conduction headset.

MORE ABOUT HEADSET OPTIONS:

Lazer-Pro | Cyber | Diamonds | SST | The Edge

Safety

1. Recycle your products
2. The WEEE logo appears on the product to indicate that this product must not be disposed of or dumped with your other household wastes. You are liable to dispose of all your electronic or electrical waste equipment by transporting to an appropriate collection point for recycling of such hazardous waste.
3. **FCC Radiation Exposure Statement:** This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.
4. **IC Warning:** This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.
5. IC Radiation Exposure Statement: This equipment complies with IC RSS-102 radiation exposure limits set forth for an uncontrolled environment. This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.
6. FCC Notice: This device complies with Part 15 of FCC rules. Operation is subject to the following 2 conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Warranty / Repairs

Porta Phone items are warrantied against defects in material and/or factory workmanship for a set period from the date of purchase. Standard repairs due to misuse or wear and tear, as well as replacement parts including but not limited to batteries, padding, USB cable, etc. are excluded. Shipping to Porta Phone is at customer's expense, Porta Phone will pay for return ground shipping if the product warranty applies to the repair. Call for details.

Shipping: Prior to returning your headset for warranty or service you must call Porta Phone for an RA (return authorization) number: 1 (800) 233-1113.

General Service: All repair work will be performed for the cost of replacement parts and return shipping from the Porta Phone factory.

Service / Porta Phone
145 Dean Knauss Drive
Narragansett, RI. 02882

www.portaphone.com
1 (800) 233-1113

PLAY CALLER

EPak-XR

Coach to Player Wireless

PORTA PHONE

www.portaphone.com
1 (800) 233-1113

EPak-XR

Coach to Player Wireless

SET-UP

1. Charging the Batteries

COACH EPak-XR

- The corresponding red LED indicates charging; when charging is complete, the LED turns solid green. Charging time is appx. 3 hours; operating time is appx. 6 hours.

PLAYER PXR Receivers

- ***Systems with up to five receivers***: Plug the USB-C cable into a power source and connect it to each TPRO-R.
- ***Systems with more than five receivers:*** Use the 12-port multi-charger. The corresponding red LED indicates charging; when charging is complete, the LED turns solid green. Charging time is appx. 3 hours; operating time is appx. 6 hours.

2. Power On System & Link Transceivers/Receivers

COACH EPak-XR

- Install charged battery, press power button to turn ON.
- Turn on headset – pairing is automatic.

PLAYER PXR Receivers

- Press the power button to turn ON. PXR will be in *speaker mode* by default.
- Press the Pairing Button. LED will flash blue.
- Power on headsets – pairing is automatic.

Power/system indicator:
Flashing Green Epak & Solid Green PXR indicates radios are linked.

3. Pairing Headsets

Headsets & Earbuds included with all new systems are *already paired to EPak-XR and PXR Receivers.*
This step is only necessary if a NEW headset is being added.

EPak-XR & Lazer-Pro

Ensure EPak-XR is turned on and in pairing mode:

- Press & Hold Power button to turn on.
- Press and hold Blue Pairing Button/LED for 3 seconds until it flashes rapidly.

Power on Lazer-Pro headset:

- Press and hold the power button on the Lazer-Pro headset until voice command says, "power on".
- The Lazer-Pro will seek wireless pairing automatically when turned on.
- LED lights flash red & blue indicating pairing mode.

The Items are PAIRED when:

- EPak-XR: Solid BLUE = PAIRED
- The Lazer-Pro: Flashes BLUE & the voice command says "connected".

PXR & The Edge or Diamonds

Ensure PXR Receiver is turned on and in pairing mode:

Press the Pairing Button LED will flash blue slowly.
Press & hold Pairing Button for 3 seconds until it flashes blue rapidly.

The Edge:

- Press / hold power button on headset, listen for voice command; "power on". The Edge seeks wireless pairing automatically.
- Red & blue flashing LED = Pairing mode.

The Items are PAIRED when:

- PXR: Solid BLUE = PAIRED.
- The Edge: Flashes BLUE & the voice command says "connected".

Diamonds:

- Diamonds power on automatically when removed from case & will seek wireless pairing automatically.
- Diamonds' LED will flash orange while pairing.

The Items are PAIRED when:

- PXR: Solid BLUE = PAIRED.
- Diamonds: Voice command says, "Connected." & LED stops flashing.